



**NEW**



The PFR-100 series, a small and high-performance programmable D.C. power supply, adopts natural convection design to dissipate heat. The fanless structure allows users to focus on their experiments and tests in a quiet environment. Fanless power supply will not suck in dust and foreign objects, therefore, PFR-100 series has a longer life cycle compared with that of power supplies with fan.

The PFR-100 series is a power supply with a five-fold rated power that allows users to self-define voltage and current under rated power conditions so as to satisfy them with wider voltage and current operational ranges. PFR-100 series, with rated 100W, provides two models: PFR-100L- maximum output voltage of 50V (at 2A) or maximum output current of 10A (at 10V); PFR-100M- maximum output voltage of 250V (at 0.4A) or maximum output current of 2A (at 50V).

The PFR-100 series provides front and rear panel output terminals. The front panel output terminal helps users shorten test lead replacement time while conducting adjustment on front panel's function keys. The rear panel output terminal facilitates an easy wiring operation for rackmount assembly. 3U height, 70mm width and 2.5KG in weight have greatly elevated PFR-100 series portability. Furthermore, the multi-drop mode allows users to control up to 31 PFR-100 series without using switch/Hub that help users save the equipment cost.

The LAN interface for PFR-100 is Ethernet port. PFR-100 also has a built-in web server and intuitive user interface. Users, via general browsers including Internet Explorer, Mozilla Firefox or Android cellular phones, can monitor PFR-100's test and measurement anywhere. Users not only can remotely monitor PFR-100 via internet, but also remotely observe and adjust their operating PFR-100s in the lab from your home. The outputs of PFR-100 series can be monitored including OVP, OCP, UVL; and the system information can be checked such as unit's serial number, firmware edition and internet setting. Users can remotely adjust PFR-100 settings, including output voltage/current, the slew rate for voltage/current, Bleeder circuit control, OCP, delayed time for output voltage and Buzzer settings.

The PFR-100 series provides special functionalities to meet test requirements for different load's characteristics. The CC priority mode can be applied for DUTs with diode characteristics to prevent DUT from being damaged by inrush current. A slow rise time for voltage can also protect DUT from inrush current, especially for tests on capacitive load. When power is off or load is disconnected, the activation of Bleeder circuit control will allow the bleeder resistor to consume filter capacitor's electricity. Without the bleed resistor, power supply's filter capacitor may still have electricity that is a potential hazard. For automatic testing equipment systems, the bleeder resistor allows PFR-100 series to rapidly discharge to prepare itself for the next operation.

## PFR-100L/100M

### FEATURES

- Constant Power Output for Fivefold Multi-Range(V&I) Operation
- Natural Convection Cooling Design (Fanless Structure)
- Preset Memory Function
- Output ON/OFF Delay Function
- CV, CC Priority Mode
- Adjustable Slew Rate For Voltage and Current
- Bleeder Circuit Control
- Protection : OVP, OCP, AC FAIL and OTP
- Support Front Panel and Rear Panel Output
- Built-in USB and RS-232/485 Interface Optional LAN+GPIB
- Web Server Monitoring and Control
- External Analog Control and Monitor Function
- Remote Sensing Function



PFR-100L Front Panel



PFR-100M Front Panel



PFR-100L Rear Panel



PFR-100M Rear Panel

### APPLICATIONS

- LED Module Test and Reliability Test
- Charging Test for Battery Cell
- DC/DC Converter Applications
- DC Motor Test Applications
- Solar Module Quality Test

## SPECIFICATIONS

	Model		PFR-100L	PFR-100M
OUTPUT RATING	Rated Output Voltage		50V	250V
	Rated Output Current		10A	2A
	Rated Output Power		100W	100W
REGULATION(CV)	Load Regulation (*2)		10mV	33mV
	Line Regulation (*1)		3mV	5mV
REGULATION(CC)	Load Regulation (*9)		10mA	3.2mA
	Line Regulation (*1)		8mA	1.2mA
RIPPLE & NOISE (*3)	Vp-p (*4)		50mV	150mV
	Vr.m.s.(*5)		4mV	15mV
	A r.m.s.		10mA	2mA
PROGRAMMING ACCURACY	Voltage	0.1% of setting +	40mV	200mV
	Current	0.2% of setting +	20mA	2mA
MEASUREMENT ACCURACY	Voltage	0.1% of reading +	40mV	200mV
	Current	0.2% of reading +	20mA	2mA
RESPONSE TIME	Rise Time (*6)	Rated load	50ms	200ms
	Fall Time (*7)	Rated load	100ms	300ms
	Transient Response Time (*8)	No load	500ms 1.5ms	3000ms 2ms
PROGRAMMING RESOLUTION	Voltage		2mV	10mV
	Current		1mA	0.1mA
MEASUREMENT RESOLUTION	Voltage		2mV	10mV
	Current		1mA	0.1mA
PROTECTION FUNCTION	Over Voltage Protection (OVP)	Setting range	5~55V	5~275V
	Over Current Protection (OCP)	Setting range	1~11A	0.2~2.2A
	Under Voltage Limit (UVL)	Setting range	0~52.5V	0~262.5V
	Over Temperature Protection (OTP)	Operation	Turn the output off.	Turn the output off.
	Low AC Input Protection (AC-Fail)	Operation	Turn the output off.	Turn the output off.
	Power Limit (Power Limit)	Operation	Turn the output off.	Turn the output off.
FRONT PANEL DISPLAY ACCURACY, 4 DIGITS	Voltage	0.1% of reading +	40mV	200mV
	Current	0.2% of reading +	20mA	2mA
ENVIRONMENT CONDITION	Operating Temperature		0 °C to 40 °C	
	Storage Temperature		-20 °C to 70 °C	
	Operating Humidity		20% to 80% RH; No condensation	
	Storage Humidity		20% to 85% RH; No condensation	
REARBACK TEMP. COEFFICIENT (After A 30 Minute Warm-up)	Voltage		100ppm/°C	
	Current		200ppm/°C	
OTHER	Analog Control		Yes	
	Interface		USB, RS-232/RS-485; Factory option: LAN/GPIB	
	AC Input		85~265VAC, 47~63Hz, single phase	
DIMENSIONS & WEIGHT	70(W)x124(H)x300(D)mm; Approx. 2.5kg			

Notes: \*1: At 85 ~ 132Vac or 170 ~ 265Vac, constant load.

\*2: From No-load to Full-load, constant input voltage. Measured at the sensing point in Remote Sense.

\*3: Measure with JEITA RC-9131B (1:1) probe

\*4: Measurement frequency bandwidth is 10Hz to 20MHz.

\*5: Measurement frequency bandwidth is 5Hz to 1MHz.

\*6: From 10%~90% of rated output voltage, with rated resistive load.

\*7: From 90%~10% of rated output voltage, with rated resistive load.

\*8: Time for output voltage to recover within 0.1% + 10mV of its rated output for a load change from 50 to 100% of its rated output current.

\*9: For load voltage change, equal to the unit voltage rating, constant input voltage.

PFR-100 Series Fanless Multi-Range D.C. Power Supply

**PFR-100□ - GL - GTL-258**

Model: □

L : 0-50V/10A/100W

M : 0-250V/2A/100W

Cable Options: □

GTL-258 : A GPIB cable including 25 pins Micro-D connector

PSU-232 : An RS-232 cable including RJ-45 connector

PSU-485 : An RS-485 cable including RJ-45 connector

GTL-246 : A USB cable for TypeA-TypeB connectors

None

Interface Options: □

□ : USB (Type B) & RS-232/RS-485 (RJ-45 connector) as default

GL : LAN & GPIB (25 pins Micro-D connector)

## ORDERING INFORMATION

**PFR-100L** Fanless Multi-Range D.C. Power Supply

**PFR-100M** Fanless Multi-Range D.C. Power Supply

## ACCESSORIES

CD (User Manual, Programming manual) x 1, Power cord, GTL-134 test lead, Accessory Packages, GTL-104A test lead (for PFR-100L only), GTL-105A test lead (for PFR-100M only)

## OPTIONAL ASSESSORIES

**GTL-258**

GPIB Cable, 2000mm

**PSU-232**

RS-232 Cable with DB9 Connector Kit

**PSU-485**

RS-485 Cable with DB9 Connector Kit

**GTL-246**

USB Cable (USB 2.0 Type A-Type B Cable)

**GRA-431-J-100/200**

Rack mount adapter (JIS) with AC 100V/200V

**GRA-431-E-100/200**

Rack mount adapter (EIA) with AC 100V/200V

**PFR-GL**

LAN+GPIB interface

Specifications subject to change without notice. PFR100LMDIC1DH



Zone Acticentre - CRT2 - CS 10210  
156/220 Rue des Famards - 59273 FRETIN  
Téléphone : 03.20.62.06.80  
Télécopie : 03.20.96.95.62  
<http://www.dimelco.com>

**GW INSTEK**  
Simply Reliable



[www.gwinstek.com](http://www.gwinstek.com)



[www.facebook.com/GWInstek](https://www.facebook.com/GWInstek)